

# User Guide - FLCT4BS

## RF Control - 4 Zone Touch Remote



### Features

- For use with all Single Colour LED Strips and compatible with Foss FLDC1S Receivers.
- Individual Zone push button dimming control.
- RF wireless technology with a control distance of up to 30 metres.
- Pair each zone with one or multiple receivers
- CR2032 battery power.

### Technical Parameters

- Output signal: RF(2.4GHz)
- Working voltage: 3VDC(CR2032)
- Working current: <5mA
- Standby current: <2µA
- Standby time: 2 years
- Remote distance up to 30m within Free Range. Please allow for 12m within areas restricted by obstacles.
- Working temperature: -30°C ~55°C
- Dimensions: L135×W40×H11mm
- Weight: 41g

### Operation

Pull out the plastic battery plate from the battery compartment located on the bottom of the remote to replace.

### Pairing Guide

Pairing your remote with each 2.4GHz RF receiver (FLDC1S) choose between two pairing methods.

- Using the "Match Key"

Match the controller with our receiver (Using the Match Key on the receiver)

1. Match: Short press the match key, then press the zone key on the remote within 5s.
2. To Delete a Match: Long press the match key on the receiver for 5s.

- At Power Up

Match the controller with our receiver (Without using the Match Key)

1. Match Switch off receiver power, then switch on power again, short press the zone key 3 times on the remote quickly within 5s after the receiver powers on, the link has been completed once the connected LED lights flash 3 times.
2. To Delete a match: Switch off power to the receiver, then switch on power again, short press the zone key you are deleting 5 times on the remote within 5s after power on, the unlink has been completed once the connected LED lights flash 5 times.

### Key Functions



### Dimensions

